

Confidea L-DI/L-CI

WIRED DISCUSSION UNIT WITH CHANNEL SELECTOR

Art. 71.98.0103 / 71.98.0113



Confidea L-DI



Confidea L-CI

## Description

The Confidea L-DI and L-CI wired unit combines a slim, contemporary design with superior sound quality resulting in an excellent intelligibility.

The units are interconnected using the daisy chain principle over Cat 5 network cabling with RJ45 connectors. The connectors are hidden in the base of the unit and the cables are held in place by two notches in the unit housing.

Setup can be accomplished in just a blink of an eye.


As input and output connections are interchangeable, installation is easy, fast and straightforward, reducing installation cost. It is the ideal system for frequently changing environments.

It allows the delegate of a conference to speak, request-to-speak and listen to the speaker in their native tongue.

The units are equipped with a microphone On/Off or request-to-speak button, a single channel selector driving two headphone outputs and a channel selection information display.

The OLED information display indicates the selected channel number, the abbreviated channel name in ISO format and a volume bar.

The chairman unit comes with an additional priority, next-in-line and system volume adjustment button.



The Confidea L-DI and L-CI units have the capability selecting up to 28 (CE2500) or 58 (CPU5500) channels depending on the central control unit used.

A screw lock connector is provided to connect a removable microphone.

As the microphone is immune against typical disturbances of mobile phones, delegates can leave their device on during the meeting. (MIC 38SL, to be ordered separately)

---

## Controls and Features

- Built-in high quality loudspeaker which is automatically muted when the microphone is active, to prevent acoustic feedback.
- Microphone On/Off or request-to-speak button with two signalling LEDs
- Two headphone outputs
- One headphone volume adjustment
- One channel Up/Down adjustment
- OLED channel and headphone volume information display
- The chairman version (L-CI) comes with a priority, next-in-line and system volume adjustment button

## Connectivity

- Two 3.5 mm jack plugs for headphones
- Two RJ45 connectors
- Screw lock socket to connect removable microphone

## Specifications

Technical Data	
Audio quality	16 bit digital
Headphone load impedance	> 32 ohm < 1k ohm
Output power	16.5 mW / 32 ohm
Power Supply	48V, over Cat5 cable
Dimensions (mm)	230(w), 130(h), 60(d)
Weight (g)	460
Color	RAL9011
Part number	Confidea L-DI 71.98.0103 Confidea L-CI 71.98.0113

## Accessories

- Removeable microphone  
MIC38SL 71.98.0050
  - Headphones  
TEL151 71.04.0151
  - Digital bus cable, Cat5 24AWG:
    - 2m ICC5/2 71.60.4002
    - 5m ICC5/5 71.60.4005
    - 10m ICC5/10 71.60.4010
    - 20m ICC5/20 71.60.4020
- Standard Ethernet patch cable AWG26 cannot be used!
- SPL5525 for connection to TCS5500 central equipment 71.67.5035